

Sr No	Product	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
1	MODULE MOUNTING STRUCTURE						
	HBL ROOF						
1)	Designing, Supplying, Fabrication & Installation of PV Mounting structure in MS Iron. The mounting structures and the civil concrete footings must be designed structurally to be suitable to withstand all static loads (weight of modules, wind loads etc) minimum wind speed pressure 40m/s with 3sec of gust pressure in harsh environment. The design submission must be as per ASTM-A36, ASTM-123 and ASCE 7-10. The mounting structure components are bonded together to guaranty potential equalization. The work is to be carried out strictly as per approved structure drawings, design and specification and the rate quoted is inclusive of the following:	Watt	102,000.00	29.50	2,550,000.00	459,000.00	3,009,000.00
a	Designing of the structure as per design specification approved by IBA Engineer. • Column/Pole Size: Minimum 4.5" x 4.5" in 12 gauge. Columns may be circular or square shape. • Primary Girder: 1.8Kg/ft & above • Secondary Girder: 1.8Kg/ft & above • Base Plate Size: 12" x 12" with 12mm thickness. • Top Plate Dimension: 6" x 6" with 6mm thickness. • Bracing Angles: 2"x2" by 1/4" thickness • Sharing Girder: Sharing of Girder not allowed in structure design. • Tilt Angle: Must be optimal for energy generation.			SOLUTION THE PROPERTY OF THE P	0/55/10		







	Material: MS Iron A306 Cross Bracing: Column to column in 3"x3" by 1/4" thickness angle iron with gusset plate cross bracing should be installed at both end of the structure to avoid sway under heavy winds. Civil Pads: RCC concrete pads, pads sizes shall be L x W x H (1' x 1' x 1') with finish plaster. Fasteners: All Allen bolts, Spring Washer, Nuts, Washer & Plate Washer must be SS304. Cleaning Platform: MS cleaning platform minimum width of 1.5' with 1.5"x1.5" angle iron in 3/16" thick with side supports. Paint: Before applying two coats of epoxy paint in smoke Gray colour, the contractor must first apply two coats of red oxide coating. Mounting Accessories: Includes brackets, Solid Midclamps & End clamps, and bolts.
b	Layout at Site approved by IBA Engineer
с	Civil work as per drawing and specification approved by IBA Engineer.
d	Placing of GI Rawal Bolts, Nuts bolts as per design & length & Details approved by IBA Engineer.
e	Tilt angle is to be maintained as per recommended.
f	The Contractor shall remove all the debris and clear the site before & after the completion of work as per IBA direction
g	The Contractor shall submit the detail technical shop drawing before execution of work.
h	After completion of the work the contractor shall submit the as built drawing.
i	All Allen bolts, nuts, bolts, washers, spring washers and screws for the project should be Stainless steel (SS 304).
j	The contractor must submit the ANSYS/SAP report prior to the project's execution.
k	Waterproofing and any other roof damage must be repaired with the approval of the IBA Engineer









2 PV MODULE		Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with
Commissioni latest tech. B Solar Module reflective hig tempered gla provision. The parameters in (a) Min Power Wp rated power (b) Junction B IP 68 (c) Connection conductor cross (d) Cable with connectors, (e) Anodized Support Bars (f) PVC duct, (support and la under PV Arra The Contractor manufacturer panel for a peyears. Contractor muse required certification. All works and according to tis specifications	ox Protection Degree, In box, 4.0mm2 Isss section, I, MC4 male and female Aluminium Frame and Clamps & Accessories, Isbels to be installed Iv. Ir shall provide I warranty for solar I riod not less than 25 Isst submit all the I cates for each PV I m manufacturer as per I materials must be I he drawings, I and supervisor I uction's and approval.	Watt	102,000.00	52.88	5,393,760.00		5,393,760.00













3	GRID-TIED INVERTER (PCU)	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
i)	Supply, Installation, Testing & Commissioning (SITC) DC/AC grid tie 3-phase inverter with data communication unit with Ethernet connection. The inverter with must be suited to any PV module configuration, and depending on the system design and installation proposed and for the future extended also. (Leading Market brand, having annual production greater than 1GW). The DC max power input rating should be at least 1.2 times of AC power at standard test condition (STC). The inverter unit shall be suitable for indoor and outdoor installations with IP65. The inverter must include the safety concepts such as (triple protection with Opti protect, electronic strings fuses, self-learning string failure detection, DC surge arrestor type (2) to ensure max availability. The inverter includes online monitoring with Wi-Fi Dongle. All works and materials must be according to the drawings, specifications and supervisor engineer instruction's and approval. Make: Sungrow/Huawei/SMA Power Rating: 110KW to 125KW.	Each / Pc	1	1,460,000.0	1,237,288.14	222,711.86	1,460,000.00
	Brief specification is as under:		M				
а	Max Input DC Voltage: 1100V						
b	MPPT Operating Voltage Range: 200V~1000V,						
с	Min 10 Independent MPPT Trackers						
d	Minimum Efficiency 98.0%,						
e	Warranty: 10 Years (Extendable to 15 Years)						
f	Minimum IP rating should be IP65				CLUTIC	×	







4	COMBINER BOX	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
а	DC COMBINER BOX						Tax (Flat)
	Supply, Installation, Testing & Commissioning (SITC) of DC box/Array Junction Box 16gauge wall mounted with all accessories for outdoor usage, proper cable glands as per cable size, slotted cable ducts should be installed for internal DC cabling. DC Combiner Box shall be provided One DC Breaker 4Pole per string. DC Breaker 4Pole 25A/32A,1000VDC, Qty=14 DC Breaker Make: ABB/Zjbeny/Dehn/Chint	Each / Pc	1	209,000.0	177,118.64	31,881.36	209,000.00
a	AC COMBINER BOX (LV PANEL)						
i)	Supply, Installation, Testing & Commissioning (SITC) of AC Combiner Box (LV Panel) with pad floor standing/Wall Mounted Locally fabricated in 16 gauge, Colour Code: RAL7035, MS Powder Coated, Copper Glands, Lugs, Phase indication lights, Tin Coated Copper Busbar for 3 Phases with colour coded heat shrinkable sleeves, Neutral & Earth with Polycarbonate cover sheet. Brass glands at bottom In & Out, CT's, Energy meter with all related accessories for outdoor usage dust proof enclosure. AC Breaker 250A,4P,MCCB,400V/415V, Qty:01 AC SPD 4Pole, 65kA with HRC Fuses Energy Meter: Janitza or Equivalent CT's: Ficco/Saci or Equivalent MCCB Make: ABB/Schneider or Equivalent SPD Make: ABB/Schneider or Equivalent HRC Fuses Make: Schnieder/ABB/Voltron or Equivalent	Each / Pc	1	300,000.0	254,237.29	45,762.71	300,000.00







5	CABLES	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with
а	DC CABLES			1 (cital)	out tax (i kit)		Tax (PKR)
	Supply, Installation & Testing of DC Cable, 1 Core 6mm2 Cu/XLPO/XLPO cable complete in all respect with accessories to connect the PV solar cells together and to the inverter directly to have a complete operational circuit, clamps, trays and cable end terminations which shall be DC plug and socket connectors. The allowable voltage drop for DC cables between PV Arrays and inverter should be less than 2%. Minimum voltage capacity 1500VDC, Highest permissible voltage conductor/conductor should be 1.5kV DC, Standard Double insulated: Cross link polyolefin, Tinned copper conductor: Cable should be Certified from TUV Approved. Standard: EN50618 Make: Pakistan Cable/Fast Cable/Kuka/ Jiukai as Engineer Approved.	Meter	2000	240.00	406,779.66	73,220.34	480,000.00
b	AC CABLES	_4					
	Supply, Installation & Testing of the power cables with all required works in different sizes of ducts/pipes, Cable lugs, Clamps and all needed fittings to connect cables terminals from source to destination with LV termination kit (Raychm). According to drawings, specifications, instructions, and demand of the supervising engineer as follow: Brand: Pakistan Cable/Fast Cable or Equivalent as IBA Engineer Approved.						
i)	4C x 120mm2,0.6/1kV Cu/PVC/PVC STD Pure Copper	Meter	25	12.005.00	202 502 50		
с	Earthing Cables			13,806.00	292,500.00	52,650.00	345,150.00
	Supply, Installation & Testing of Earthing Cable, Including uPVC Pipe with related accessories. Brand: Pakistan Cable/Fast Cable or Equivalent as Engineer Approved.						
i)	1 core 2.5 sqmm, CU/PVC/FLEX (Green)	Meter	540	61.95	28,350.00	5,103.00	33,453.00
	1 core 4 sqmm, CU/PVC/FLEX (Green)	Meter	180				
ii)	2 core + squim, coyl veyl LEX (dieen)			158.32	24,150.00	4,347.00	28,497.00











6	EARTHING SYSTEM	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
	Supply, Installation, testing and commissioning of Earth Electrodes (Rod Type) for Earthing System with 25mm Dia 3 meters (10feet) long driven Pure copper Solid rod, complete with clamps lugs, washer/bolts, connected with 1x70mmsq bare copper 50mm diaG.I pipe/UPVC pipe class 'D/E' up to Earth chamber, job includes cad-welding of copper conductor to earth electrode rod at one end and provision/fixing of cable lugs at other end, including all accessories and RCC inspection chamber, heavy duty G.I. Cover having earth symbol, etc as per the specifications and Drawings and to the entire satisfaction and approval of the Engineer. Minimum depth of the earth pit should be less than 1 Ohm for AC/DC/LA		3	88,500.0	225,000.00	40,500.00	265,500.00
7	DATA LOGGER REMOTE MONITORIN	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
	Supply, installation, testing and commission of data Manager with Remote Monitoring System consists of the following parameter: a) Total energy generation of PV Plant b) Instantaneous Power been generated by solar PV plant c) Current load of client d) Load profile v/s energy generation. e) Daily Solar Plant generation report in PDF from Data should be store on server for not more than 10 min time interval. Data must be access through internet via user friendly GUI.	Each / Pc	1	170,000.00	144,067.80	25,932.20	170,000.00











8	CABLE TRAY	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
i)	Supply and installation of following sizes 16SWG heavy Duti HDGI Perforated/Non- Perforated as per site requirement. Cable Tray 150mm x 100mm with 16 SWG HDGI. Complete with all installation material such as angle iron support of size, MS round bar, elbows, Tee, Nuts, Bolts, Washer, Hilti drop-in anchour, etc. Complete in all respect, as per the specification and drawings.	Meter	100	1,531.64	129,800.00	23,364.00	153,164.00
9	CIVIL & MISCELLANEOUS WORK	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
i}	Supply and installation of 2-inch UPVC conduit sockets, Bends, Elbows, T-Joints, G.I Clamps, complete in all respects.	Meter	100	703.16	59590.00	10726.20	70316.20
ii)	Supply and installation of 1-inch UPVC conduit sockets, Bends, Elbows, T-Joints, G.I Clamps, complete in all respects.	Meter	80	350.88	23788.80	4281.98	28070.78
iii)	Construct of concrete manholes/cable chambers (900mm x 900mm x 900mm deep) with heavy duty RCC covers with anti-rust paint, including all required sleeves for pulling underground power cables laid in pipes.	Each	1	27,848.00	23,600.00	4,248.00	27,848.00
iv)	Re-fixing pavers/Tiles as in position including providing sand etc.	Job	1	27,848.00	23,600.00	4,248.00	27,848.00
v)	Supply & Installation of Inverter & LV Panel fiber shed as per Engineer instructions and approval.	Each	1	69,620.00	59,000.00	10,620.00	69,620.00













NET METERING	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges for Electrical Load Inspector NOC etc. Only the cost of K.Electric/Nepra Challan shall be paid by IBA	Job	1	793,500.0	690,000.00	103,500.00	793,500.00
FUEL SAVER CONTROLLER	Unit	Qty	Unit Price (PKR)	Amount with out Tax (PKR)	Tax Amount (PKR)	Amount with Tax (PKR)
Design, Supply, Installation, testing and commissioning of Deif/Encombi or Equivalent Fuel Saver Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should performs the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the load and grid status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters e) Internal logging of all relevant system data f) Provision of relevant system data f) Provision of relevant system data for local and remote monitoring g) Emergency shutdown of the PV inverters in case of a system malfunction h) Online Dashboard access to monitor solar power plant, Gensets	Each	1	800,000.0	677,966.10	122,033.90	800,000.00
	Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges for Electrical Load Inspector NOC etc. Only the cost of K.Electric/Nepra Challan shall be paid by IBA FUEL SAVER CONTROLLER Design, Supply, Installation, testing and commissioning of Deif/Encombi or Equivalent Fuel Saver Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should performs the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the load and grid status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters elipse of all relevant system data f) Provision of relevant system data f) Provision of relevant system data for local and remote monitoring g) Emergency shutdown of the PV inverters in case of a system malfunction	Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges for Electrical Load Inspector NOC etc. Only the cost of K.Electric/Nepra Challan shall be paid by IBA FUEL SAVER CONTROLLER Design, Supply, Installation, testing and commissioning of Deif/Encombi or Equivalent Fuel Saver Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should performs the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the load and grid status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters e) Internal logging of all relevant system data f) Provision of relevant system data for local and remote monitoring g) Emergency shutdown of the PV inverters in case of a system malfunction	Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges for Electrical Load Inspector NOC etc. Only the cost of K.Electric/Nepra Challan shall be paid by IBA FUEL SAVER CONTROLLER Design, Supply, Installation, testing and commissioning of Deif/Encombi or Equivalent Fuel Saver Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should performs the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the load and grid status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters e) Internal logging of all relevant system data f) Provision of relevant system data f) Provision of relevant system data f) Provision of relevant system malfunction	Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges for Electrical Load Inspector NOC etc. Only the cost of K.Electric/Nepra Challan shall be paid by IBA FUEL SAVER CONTROLLER Design, Supply, Installation, testing and commissioning of Deif/Encombi or Equivalent Fuel Saver Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should performs the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the load and grid status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters e) Internal logging of all relevant system data for local and remote monitoring g) Emergency shutdown of the PV inverters in case of a system malfunction	Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges for Electrical Load Inspector NOC etc. Only the cost of K.Electric/Nepra Challan shall be paid by IBA FUEL SAVER CONTROLLER Design, Supply, Installation, testing and commissioning of Deif/Encombio or Equivalent Fuel Saver Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should performs the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the load and grid status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters e) Internal logging of all relevant system data for local and remote monitoring g) Emergency shutdown of the PV inverters in case of a system malfunction	Service of Net metering application process for extension of new system & existing solar system at IBA City campus handling as per K.E. approved criteria complete in all respects or directed by Engineer. This also include the services charges & fee for assessment of Grid load flow study of IBA City campus & service charges of Electrical Load Inspector NOC etc. Only the cost of K. Electric/Nepra Challan shall be paid by IBA FUEL SAVER CONTROLLER Unit Qty Unit Price (PKR) Tax Amount (PKR) FUEL SAVER CONTROLLER Unit Qty Unit Price (PKR) Tax Amount (PKR) Tax Amount (PKR) Tax Amount (PKR) Tax Amount (PKR) Controller System Solution for the Integration of PV Power Plant into Electrical Network based on Gensets. Fuel Save controller should perform the following tasks: a) Monitoring of the genset's power and operating status b) Monitoring of the genset's power and operating status c) Calculation of suitable values for the maximum power output of the PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters according to defined parameter settings and the current status of gensets and load d) Control and communication interface to PV inverters e) Internal logging of all relevant system data for local and remote monitoring g) Emergency shutdown of the PV inverters in case of a system maffunction





Two years of operations and maintenance is an integral activity of this EPC project, which will determine the success of this project. It is to be noted that 2 years 0.8.M will be initiated after project close to intended that the project performs as aper design Performance. Commitment Table" while also maintaining the project to ensure reliability and longerity for 25 years, industry best practices to be used to operate and maintain the solar PV Project. All necessary preventive and corrective actions to be shared and implemented before the start of the OSM contract. The following key performance metrics to be monitored and reported which are as follows: Cleaning of solar panels to remove dirt, dust, and debris. Inspection of cables, connectors, junction boxes, and grounding systems. Tightening of bolts, screws, and clamps in mounting structures. I dentifying and resolving faults in moudules, invertes, or other components. Rapid response to critical failures to minimize downtime. Tracking key performance indicators (KPs) such as energy output, PR (performance ratio), and system availability. Implementing software updates for inverters and monitoring systems. Managing claims for defective components under warranty, implementing software updates for inverters and monitoring systems. Managing claims for defective components under warranty, implementing and maintaining safety measures for OSM personnel. Performance Ratio (Junn test) to be carried out for 15 days once project is completely installed and ready for testing. Monity reports to be shared covering all aspects of solar PV performance induding an event log. Any system under performance or failure of an equipment will automatically trigger the requirement of a detailed root cause analysis RCA (Dased on site-based tests) and a report will have to be submitted at the earliest completion of an RCA. Note: Contractor should only submit the 10x8WP Performance in the contractor of the performance in the contractor of the performance in the contractor of	2 OPERATION & MAINTENANCE	Unit	Qty	Unit Price (PKR)	Amount with	Tax Amount (PKR)	Amount wit
the 102kWp Performance	Two years of operations and maintenance is an integral activity of this EPC project, which will determine the success of this project. It is to be noted that 2 years O&M will be initiated after project closet is intended that the project performs as per design "Performance Commitment Table" while also maintaining the project to ensure reliability and longevity for 25 years. Industry best practices to be used to operate and maintain the solar PV Project. All necessary preventive and corrective actions to be shared and implemented before the start of the O&M contract. The following key performance metrics to be monitored and reported which are as follows: • Cleaning of solar panels to remove dirt, dust, and debris. • Inspection of cables, connectors, junction boxes, and grounding systems. • Tightening of bolts, screws, and clamps in mounting structures. • Identifying and resolving faults in modules, inverters, or other components. • Rapid response to critical failures to minimize downtime. • Tracking key performance indicators (KPIs) such as energy output, PR (performance ratio), and system availability. • Implementing software updates for inverters and monitoring systems. • Managing claims for defective components under warranty. • Implementing and maintaining safety measures for O&M personnel. Performance Ratio (burn test) to be carried out for 15 days once project is completely installed and ready for testing. Monthly reports to be shared covering all aspects of solar PV performance including an event log. Any system under performance or failure of an equipment will automatically trigger the requirement of a detailed root cause analysis RCA (based on site-based tests) and a report will have to be submitted at the earliest completion			(PKR)	514,500.0	77,175.0	Amount wi Tax (PKR)
	Tax	Amount					011,096.43 334,985.56
	ıax	AMOUNT				1 :	224 925 56

Grand Total Amount of in Words:

Rupees: Fourteen million, three hundred forty-six thousand, eighty-one rupees and ninety-eight paisas only.





#301 ×